

Intrinsically Safe - Dust RIPS® SERIES E502	Part Number Coding						
	E502	Travel	A	Y	Conn / Cable end	Option 1	Option 2

Small Angle Industrial Rotary Sensor		
Travel		
degrees rotation	5° to 15°	Value
Electrical Interface Options		
Input	Output	
+ 5 V dc	See below	A
Calibration Adjusters		
Sealed Trim Pots		Y
Connector / Cable		
Connector - Axial IP67		J
Cable - Axial Gland IP67	Please specify cable length in cm.	Lxx
eg. L2000 specifies 20 metres of cable with an axial cable gland		
OPTIONS		
Spring Return		
Fitted		N
Housing		
Flanged	Standard option no code	Blank
Servo Mount		P

Please Note: This sensor *must* be used with a Galvanic Isolation Amplifier - See X005 sheet for Out